




Steps in the Application of Scenario 15

1	Avatar of player begins front of the engine room.	
2	Player goes to MOP	
3	Read messages about alarm on MOP screen	
4	Press Acknowledge button	
5	Go in front of GSP generators synchronization panelboard just behind MOP	
6	Check that G1 is running on load and press G2's start button	

7	Check F1 & F2 values. Raise or lower F2 by pushing GM2's increase or decrease speed buttons.	
8	Switch on the SY selector to No2	
9	Watch the SY needle's rotation. Increase or decrease the speed of GM2 by pushing speed buttons.	
10	Push the ACB2/On Button at 12 o'clock.	
11	Select position OFF at the synchronizing selector, immediately after the ACB2 closes	
12	Finish.	

